

REMARKS

Enclosed herewith is a Substitute Specification in which the specification as filed has been amended in various places to correct typographical and grammatical errors, and also to add section headings.

In support of the above, enclosed herewith is a copy of the specification as filed marked up with the above changes.

The undersigned attorney asserts that no new matter has been incorporated into the Substitute Specification.

The claims have been amended to more clearly define the invention as disclosed in the written description. In particular, the claims have been amended for clarity.

Applicants believe that the above changes answer the Examiner's 35 U.S.C. 112, paragraph 2, rejection of the claims, and respectfully requests withdrawal thereof.

The Examiner has rejected claim 8 under 35 U.S.C. 102(b) as being anticipated by Applicants' Admitted Prior Art (AAPA), and under 35 U.S.C. 102(e) as being anticipated by U.S. Patent 6,446,037 to Fielder et al. The Examiner has further rejected claims 1, 2, 4, 6 and 7 under 35 U.S.C. 103(a) as being unpatentable over AAPA in view of Fielder et al.

AAPA (i.e., Fig. 1) discloses a prior art multi-channel audio signal processing device in which audio signals in the form of n frequency sub-band signals are applied to n synthesis filter

banks and then combined in a combination circuit C for forming a reproduction channel.

Fielder et al. discloses, at col. 7, lines 28-34, an audio signal being decoded to form corresponding sub-band signals, and the sub-band signals being filtered by a synthesis filter bank to produce an output signal.


Applicants submit that the synthesis filter bank in Fielder et al. is substantially similar to that disclosed in Fig. 1, i.e., the sub-band signals in CH1 are applied to a first synthesis filter bank SFB1, the sub-band signals in CH2 are applied to a second synthesis filter band SFB2, etc.

In the subject invention, as claimed, the sub-band signals are first combined, and then the combination signals are subjected to synthesis filtering. As such, significantly fewer synthesis filter means are needed resulting in a significant reduction in cost.

Applicants believe that the subject invention, as claimed, is neither anticipated nor rendered obvious by the prior art, either individually or collectively, and as such, is patentable thereover.

Applicants believe that this application, containing claims 1-8, is now in condition for allowance and such action is respectfully requested.

Respectfully submitted,

by 
Edward W. Goodman, Reg. 28,613
Attorney
Tel.: 914-333-9611

CERTIFICATE OF MAILING

It is hereby certified that this correspondence is being deposited with the United States Postal Service as First-class mail in an envelope addressed to:

COMMISSIONER OF PATENTS AND TRADEMARKS
P.O. BOX 1450
ALEXANDRIA, VA 22313-1450

On December 8, 2003
By Burnett James

#11(NE)
B.D.
12/22/07

MULTI-CHANNEL AUDIO SIGNAL PROCESSING DEVICE

BACKGROUND OF THE INVENTION

Field Of The Invention

[0001] The invention relates to a multi-channel audio signal processing device ~~provided including with~~ signal supply means for
5 supplying coded audio signals through several input channels, and for each input channel, through separate sub-channels which cover distinct frequency sub-band domains, and ~~provided with~~ including one or several synthesis or reconstruction filters (SFB) for decoding and synthesizing audio signals over the total frequency domain
10 covered by the sub-band domains.

Description Of The Related Art

[0002] It is usual, in this case, to include filter means, such as main-related filters or ~~sound~~ sound-widening filter means of a
15 different kind, downstream of the synthesis or reconstruction filters in the signal transport direction, i.e., after the reconstruction of the broadband audio signals. The same number of synthesis or reconstruction filters will then be present as there are input channels. The main-related filters or ~~sound~~ sound-
20 widening filter means of a different kind, also referred to as "incredible sound filters (ISF)", are then constructed as broadband filters ~~then~~. Instead of such "incredible sound filters", alternative filter means may be provided in the audio signal

processing device, such as, for example, equalization or different tone control filters; ~~to~~. These, too, will be provided downstream of the synthesis or reconstruction filters.

5

SUMMARY OF THE INVENTION

[0003] The invention has for its object to simplify such an audio signal processing device without detracting from the quality of the sound reproduction.

10 [0004] According to the invention, the multi-channel audio signal processing device as defined in the opening paragraph is characterized in that the device further comprises sub-band combination circuits ~~are present~~, each sub-band combination circuit being supplied with audio signals through respective input channels which lie in one and the same sub-band frequency domain, while the
15 output signals of a sub-band combination circuit covering an associated frequency sub-domain are supplied to a synthesis filter. This means that only one synthesis or reconstruction filter is necessary for each sound reproduction channel, independently of the number of input channels. For example, if audio signals are offered
20 to seven input channels, whereas the sound is reproduced through no more than two sound reproduction channels ~~—, e.g.,~~ as a result of virtual spatial widening ~~—~~, only two synthesis or reconstruction filters are necessary, instead of seven as required in the known audio signal processing devices. In a usual stereo sound
25 reproduction, for example, only 2 or 2.1 synthesis or

reconstruction filters are necessary for 5.1 MPEG input channels. It is usual, in audio signal processing devices, as noted above, to include filter means, such as main-related filters or ~~sound-sound-~~widening filter means of a different type, downstream of the synthesis or reconstruction filters as seen in the signal transport direction. It is also possible to provide, for example, equalization filters in this manner.

5 [0005] According to the invention, however, it becomes possible to provide filtering means upstream of the synthesis filters as seen in the transport direction. These filter means may then be of a narrow-band type and may, accordingly, be of a simpler construction.

15 [0006] It is thus possible for the filter means to be included in the connection between associated sub-band combination circuits and a synthesis filter. An equal filtering then takes place for all audio signals supplied through the input sub-channels covering the same frequency sub-domain, which results in an equal filtering of the audio signals supplied through the respective input channels. The filter means may comprise, for example, equalization or 20 different tone control filters in a filtering mode as described above.

[0007] It is also possible for the filter means to be included in the input sub-channels. The filter means may then be of a particularly simple construction; ~~i.~~ It then becomes possible, in 25 particular, to form the filter means by elements which introduce a

scale factor. Irrespective of the location where the filter means
are is positioned, the filter means may, in either case, comprise
narrow-band filters for obtaining a desired virtual spatial
widening from which the audio signals can be heard through distinct
5 reproduction channels.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] The invention will now be explained in more detail with
reference to the accompanying drawings, in which:

10 [0009] Fig. 1 shows an audio signal processing device according
to the present state of the art;

[0010] Fig. 2 shows a first embodiment of an audio signal
processing device according to the invention, shown for only one
sound reproduction channel;

15 [0011] Fig. 3 shows a second embodiment of an audio signal
processing device according to the invention, shown for only one
sound reproduction channel; and

[0012] Fig. 4 shows a third embodiment of an audio signal
processing device according to the invention for 2.1 input
20 channels, only one sound reproduction channel being depicted.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0013] In the multi-channel audio signal processing device shown
in Fig. 1, the input signals are derived from a frequency sub-band
25 encoded storage medium, such as, for example, an optical disc or a

DCC (digital compact cassette), or from a transmission system. The audio signals laid down on this medium or transmitted are distributed over separate channels, and are distributed within each channel over separate frequency sub-bands in accordance with known encoding techniques by means of analysis filter banks. See, for example, "Ken C. Pohlmann, Principals of Digital Audio, 3rd ed., McGraw-Hill Inc., 1995" on this subject. The coded signals obtained from the storage medium or through transmission are supplied through channels CH1, CH2, ..., CHn to synthesis filter banks SFB1, SFB2, ..., SFBn. The supplied signals are decoded by ~~means of~~ these synthesis filter banks, and audio signals are obtained over the total frequency domain covered by the sub-band domains. These broadband audio signals are joined together via main-related filters ISF1, ISF2, ..., ISFn, and ISF1', ISF2', ..., ISFn' by ~~means of~~ combination circuits C and conducted to the sound reproduction means of the reproduction channels present, i.e. in the embodiment shown to two stereo reproduction channels L and R.

[0014] In the embodiment of the invention as shown in Fig. 2, the coded signals originating from the storage medium or obtained through transmission are supplied to sub-band combination circuits SBS1, SBS2, ..., SBSn through the channels CH1, CH2, ..., CHn. The output signals of these sub-band combination circuits are supplied through respective equalization filters H1, H2, ..., Hn to the synthesis filter SFB, and from there to the sound reproduction

means of a reproduction channel—present. Although this is not shown in Fig. 2, said output signals may also be supplied to a further synthesis filter through equalization filters, and from there to the sound reproduction means of a further reproduction channel.

5 [0015] In the embodiment of the invention as shown in Fig. 3, the coded signals, originating from the storage medium or obtained through transmission, are combined in accordance with frequency sub-bands through filters ISF11, ISF12, ..., ISF1k; ISF21, ISF22, ..., ISF2k; ...; ISFn1, ISFn2, ..., ISFnk present in all sub-
 10 channels of the individual input channels, i.e., in accordance with ISF11, ISF21, ..., ISFn1; ISF12, ISF22, ..., ISFn2; ...; ISF1k, ISF2k, ..., ISFnk, by means of respective sub-band combination circuits SBS1, SBS2, ..., SBSn, and supplied to a synthesis filter bank SFB. The supplied channels are coded by means of this
 15 synthesis filter bank and audio signals are obtained, again covering the total frequency domain corresponding to the sub-band domains. These audio signals are subsequently conducted to the sound reproduction means of a corresponding reproduction channel (L). A stereo sound reproduction can be obtained in that the input
 20 signals of the audio signal processing device are also supplied to a second circuit identical to the one depicted in Fig. 3, and in that subsequently, the audio signals obtained by means of this circuit are supplied to the sound reproduction means of a second reproduction channel R. If a sufficiently fine subdivision into
 25 frequency domains is achieved in this embodiment of the invention,

PHN 17,835

the filters ISF can be given a comparatively simple construction. It was found that the provision of no more than scale factors is sufficient.

[0016] In the embodiment shown in Fig. 4, the coded signals, originating from the storage medium or obtained through transmission, are supplied through 2.1 channels, i.e., through 2 channels covering the entire bandwidth and a so-called "low frequency enhancement (LFE) channel". The signals supplied through the two channels covering the full bandwidth are conducted through "incredible sound filters" ISF11, ISF12, ..., ISF1n, and ISF21, ISF22, ..., ISF2n to the respective sub-band combination circuits SBS1, SBS2, ..., SBSn, whereas the signals supplied through the LFE channel are only supplied to the sub-band combination circuits SBS1 and SBS2 which cover the lowest frequency sub-band domains. The output signals of the sub-band combination circuits are again supplied to a synthesis filter SFB ~~again~~. The output signals of this synthesis filter are subsequently passed on to the sound reproduction means of a corresponding reproduction channel (L). It is true, again, that a stereo sound reproduction can be obtained in that the input signals of the audio signal processing device are also supplied to a second circuit identical to the one depicted in Fig. 4, and in that subsequently, the audio signals obtained by means of this circuit are supplied to the sound reproduction means of a second reproduction channel R. If a usual 5.1 channel arrangement is necessary in this case, three more channels are to

PHN 17,835

be added in this embodiment in a manner as shown in Fig. 3. Five virtual sound reproduction sources may then be created by means of two sound reproduction channels.

[0017] It will be obvious from the above that any number of
5 input channels required may be combined with any number of sound reproduction channels, which may or may not be virtual. Neither are the filter means limited to the "incredible sound filters" and equalization filters mentioned here; it is alternatively possible to construct the filter means as a volume control, especially in a
10 configuration as shown in Fig. 2. The filter means, moreover, may be chosen to be fixed ones or adjustable ones.

ABSTRACT+ OF THE DISCLOSURE

An audio signal processing device ~~comprises~~ includes a
signal supply ~~means to supply~~ for supplying coded audio signal over
5 more than one input channel and, per input channel, over separate
frequency sub_bands domain sub_channels ~~coded audio signals~~.

————Further filters are used to decode and synthesize the
audio signals over the total frequency domain.

————Sub_band combination circuits are used for supplying
10 respective input channels to the same sub_band combination circuit
the signals from the same sub_band frequency domain audio signals.

~~Fig. 1~~